



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

SIP Feature Server Administration Guide

Starting Feature Server

12/19/2025

Starting Feature Server

To start and verify SIP Feature Server:

Warning

Do not start Feature Server until you have set the configuration options *replicationStrategyClassName* and *replicationOptions*. See [Cassandra options](#).

1. To run Feature Server in secure (https) mode:
 - Open the `start.ini` file and uncomment `etc/jetty-ssl.xml`
 - In the IVR Profile, set `initial-page-url` = `https://Feature Server IP address or host name:8443/fs`
2. Use Genesys Administrator, not the command line, to start SIP Feature Server. If you are running more than one Feature Server, start the Master first.
3. In Genesys Administrator, verify that the Feature Server is running.
4. Verify that the GAX interface is running by logging in as the Default administrator (in other words, the Default user in Configuration Server):
`GAX IP address:port/gax`
5. At this point, only the Default administrator can log into the Feature Server GAX interface. To enable other users to log in as administrators, [assign the Administrator role](#) to them.