



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

GRS Log Events

GRS Log Events/Alarms

GRS Log Events/Alarms

The following log events/alarms are used in Genesys Rules System.

Code	Type	Type Detail	Text/Explanation
21300	ALARM	BRS_ERROR_MESSAGE	%s Application entry not found in bootstrapconfig.xml for application id XXX Explanation: This is a configuration error with GRAT/GRE, the application entry could not be located in the bootstrapconfig.xml file.
21324	ALARM	BRS_ERROR_MESSAGE	%s Received null response Explanation: There is a connectivity issue between GRAT/GRE and the Configuration Server. GRAT/GRE is unable to send messages to Configuration Server.
21325	ALARM	BRS_ERROR_MESSAGE	%s Received error from Configuration Server: xxx, yyy Explanation: There is a connectivity issue between GRAT/GRE and the Configuration Server. GRAT/GRE received an error "xxx" when receiving data from Configuration Server.
21342	ALARM	BRS_ERROR_MESSAGE	%s Run time exception XXX Explanation: A runtime exception occurred when communicating with Configuration Server. The details of the message(s) will be shown in 'XXX'
21351	ALARM	BRS_ERROR_MESSAGE	%s Could not connect to the primary configuration server XXX and a backup configuration server was not defined. Explanation: A failure

Code	Type	Type Detail	Text/Explanation
			occurred connecting to the primary Configuration Server specified in bootstrapconfig.xml, and since no backup Configuration Server was defined, this alarm was issued.
21352	ALARM	BRS_ERROR_MESSAGE	%s Could not connect to the primary configuration server XXX Explanation: A failure occurred connecting to the primary Configuration Server specified in bootstrapconfig.xml. The backup Configuration Server will be attempted.
21359	ALARM	BRS_ERROR_MESSAGE	%s Could not connect to the backup server XXX Explanation: A failure occurred connecting to the primary Configuration Server specified in bootstrapconfig.xml. Connection to the backup Configuration Server was attempted, but failed.
21363	ALARM	BRS_ERROR_MESSAGE	%s connect(): caught exception while opening connection to server 'XXX'. Nested exception: 'YYY' Explanation: A protocol exception occurred communicating to server (XXX). Details are provided in exception text (YYY)
21368	ALARM	BRS_ERROR_MESSAGE	%s ServerListener: caught exception on handleMessage: "XXX" Explanation: An unexpected exception occurred when handling a message from Configuration Server. The details are provided in (YYY).
21369	ALARM	BRS_ERROR_MESSAGE	%s processMessage(): message is lost because message receiver is full

Code	Type	Type Detail	Text/Explanation
			Explanation: A message from Configuration Server to GRAT/GRE was lost because the message receiver queue was full.
21380	ALARM	BRS_ERROR_MESSAGE	%s Caught exception while submitting request ["XXX"] to server: YYY Explanation: A protocol exception occurred when submitting a request message (XXX) to Configuration Server (YYY).
21393	ALARM	BRS_ERROR_MESSAGE	%s Caught exception while opening connection to server 'XXX'. Nested exception: YYY Explanation: An unexpected exception occurred connecting to Configuration Server XXX, details are provided in YYY.