



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Genesys Voice Platform

MRCP Proxy

4/10/2025

MRCP Proxy

Options for this component are contained in the following configuration sections:

- [ems](#)
- [log](#)
- [snmp](#)
- [stack](#)
- [vrmpoxy](#)

Tip

In the summary table(s) below, type in the Search box to quickly find options, configuration sections, or other values, and/or click a column name to sort the table. Click an option name to link to a full description of the option. Be aware that the default and valid values are the values in effect with the latest release of the software and may have changed since the release you have; refer to the full description of the option to see information for earlier releases.

Power users: [Download a CSV file](#) containing default and valid values and descriptions.

The following options are configured at the application level (in other words, on the application object).

Section	Option	Default	Changes Take Effect
ems	logconfig.MFSINK	*	immediately
ems	metricsconfig.MFSINK	*	immediately
ems	ors.reportinginterval	60	At start/restart
ems	rc.amq_connection_send_timeout	60	At start/restart
ems	rc.cdr.batch_size	500	At start/restart
ems	rc.cdr.local_queue_max	-1	At start/restart
ems	rc.cdr.local_queue_path	cdrQueue_rm.db	At start/restart
ems	rc.certificate		at start/restart
ems	rc.keystore_certificate		at start/restart
ems	rc.keystore_password		at start/restart
ems	rc.ors.batch_size	500	At start/restart
ems	rc.ors.local_queue_max	-1	At start/restart
ems	rc.ors.local_queue_path	orsQueue_rm.db	At start/restart
ems	rc.truststore_certificate		at start/restart
Section	Option	Default	Changes Take Effect

Section	Option	Default	Changes Take Effect
log	all	../logs/MRCPProxy	immediately
log	check-point	1	immediately
log	compatible-output-priority	false	immediately
log	debug	../logs/MRCPProxy	immediately
log	expire	20	immediately
log	interaction	../logs/MRCPProxy	immediately
log	keep-startup-file	false	After restart
log	memory		immediately
log	memory-storage-size		When memory output is created
log	messagefile		Immediately, if an application cannot find its *.lms file at startup
log	message_format	short	immediately
log	print-attributes	false	immediately
log	segment	10000	immediately
log	spool		immediately
log	standard	../logs/MRCPProxy	immediately
log	time_convert	local	immediately
log	time_format	ISO8601	immediately
log	trace	../logs/MRCPProxy	immediately
log	verbose	standard	immediately
snmp	timeout	100	At start/restart
stack	connection.portrange	10000-11999	At start/restart
stack	connection.timeout	10000	At start/restart
stack	trace.debug	true	At start/restart
vrmpoxy	disconnect_ping_timeout	true	Immediately
vrmpoxy	fips_enabled	false	After restart
vrmpoxy	ping_alarm_threshold	3	Immediately
vrmpoxy	resource_alarm_threshold	30	Immediately
vrmpoxy	timeout.back_in_service	10000	Immediately
vrmpoxy	timeout.barge_in_occurred	10000	Immediately
vrmpoxy	timeout.check_avail_res	30000	Immediately
vrmpoxy	timeout.clean_loop	60000	Immediately
vrmpoxy	timeout.close_session	10000	Immediately
vrmpoxy	timeout.control	10000	Immediately
vrmpoxy	timeout.define_grammar	10000	Immediately
Section	Option	Default	Changes Take Effect

Section	Option	Default	Changes Take Effect
vrmproxy	timeout.get_params	10000	Immediately
vrmproxy	timeout.get_result	10000	Immediately
vrmproxy	timeout.get_server_info	10000	Immediately
vrmproxy	timeout.max_idle	180000	Immediately
vrmproxy	timeout.open_session	10000	Immediately
vrmproxy	timeout.pause	10000	Immediately
vrmproxy	timeout.recognize	10000	Immediately
vrmproxy	timeout.recog_start_timers	10000	Immediately
vrmproxy	timeout.reconnect_interval	10000	Immediately
vrmproxy	timeout.resume	10000	Immediately
vrmproxy	timeout.set_params	10000	Immediately
vrmproxy	timeout.speak	10000	Immediately
vrmproxy	timeout.stop	10000	Immediately
vrmproxy	uri	rtsp://localhost:16000/ mrcpproxy	After restart
Section	Option	Default	Changes Take Effect
