



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Configuration Layer Objects Reference Guide

CfgErrorType

CfgErrorType

Values

Mnemonic	ID	Flag	Short Description	Log Name
CFGNoError	0	0	'Success'	CFGNoError
CFGServerNotFound	1	0	'SCEE018 - The specified Configuration Server cannot be found. Check the Host name and Port under Details and try again.'	CFGServerNotFound
CFGWrongProtocol	2	0	'SCEE001 - Your application cannot connect to Configuration Server because it is using a wrong communication protocol. Check the Release Notes for version compatibility information.'	CFGWrongProtocol
CFGUnknownMessage3		0	'SCEE002 - The application message cannot be identified as a valid message by the Configuration Server. Check the Release Notes for version compatibility information.'	CFGUnknownMessage
CFGLoginIncorrect	4	0	'SCEE003 - Invalid logon information specified. Check your User name and Password and try again.'	CFGLoginIncorrect
CFGNoDBAccess	5	0	'SCEE005 - The link to the Configuration Database is not	CFGNoDBAccess

Mnemonic	ID	Flag	Short Description	Log Name
			available. Contact your network administrator.'	
CFGDBError	6	0	'SCEE006 - A database error has occurred. Try the same transaction again. If the problem persists, contact your network administrator.'	CFGDBError
CFGAppSecurityViolation	7	0	'SCEE004 - Your application is not recognized by the Configuration Server. Check the Application name under Details and try again.'	CFGAppSecurityViolation
CFGAccessDenied	8	0	'SCEE007 - Access denied. Please contact Technical Support.'	CFGAccessDenied
CFGNoPermission	9	0	'SCEE008 - Permission error. Your access privileges are insufficient for performing the requested transaction.'	CFGNoPermission
CFGObjectNotFound	10	0	'SCEE009 - Object does not exist. Another client may have modified or deleted the specified object.'	CFGObjectNotFound
CFGListItemNotFound	11	0	'SCEE010 - Object association does not exist. Another client may have modified or deleted the specified object association.'	CFGListItemNotFound
CFGUniquenessViolation	12	0	'SCEE011 - Duplicate information specified. The specified	CFGUniquenessViolation

Mnemonic	ID	Flag	Short Description	Log Name
			information is duplicated within the current scope.'	
CFGDependentObject13		0	'SCEE012 - Additional action required. An additional action is necessary to complete the requested transaction.'	CFGDependentObjects
CFGIncompleteObjectData		0	'SCEE013 - Incomplete data or the specified information is not within the allowable range.'	CFGIncompleteObjectData
CFGIncorrectReference15		0	'SCEE014 - Your transaction conflicts with existing data. Check the data integrity rules for the object property specified in this error message.'	CFGIncorrectReferences
CFGUnchangeableInfo16		0	'SCEE015 - Invalid update attempt. The specified data item may not be changed or deleted.'	CFGUnchangeableInfo
CFGValueOutOfRange17		0	'SCEE016 - Incomplete data or the specified information is not within the allowable range.'	CFGValueOutOfRange
CFGUnspecifiedModification18		0	'SCEE017 - Unspecified modification. Another user may have just performed the identical transaction.'	CFGUnspecifiedModification
CFGDBResponseTimedOut19		0	'SCEE019 - The database query timeout expired. Try the transaction again. If the	CFGDBResponseTimedOut

Mnemonic	ID	Flag	Short Description	Log Name
			problem persists, contact the network administrator.'	
CFGWrongAPIParameters	20	0	'SCEE020 - Compatibility error. Please contact Genesys Technical Support.'	CFGWrongAPIParameters
CFGConnWriteError	21	0	'SCEE021 - A communication error has occurred during an attempt to send a response or notification from Configuration Server. Check the network connection and restart the application. If the problem persists, contact the network administrator.'	CFGConnWriteError
CFGConnReadError	22	0	'SCEE022 - A communication error has occurred during the receipt of a response or notification from Configuration Server. Check the Network connection and restart the application. If the problem persists, contact the network administrator.'	CFGConnReadError
CFGConfigFileNotRead	23	0	'SCEE023 - Compatibility error. Please contact Genesys Technical Support.'	CFGConfigFileNotRead
CFGConfigFileIncorrect	24	0	'SCEE024 - Compatibility error. Please contact Genesys Technical Support.'	CFGConfigFileIncorrect
CFGObjectPackingError	25	0	'SCEE025 - The	CFGObjectPackingError

Mnemonic	ID	Flag	Short Description	Log Name
			object cannot be packed for transmission because of object size limitations. Check the Release Notes for version compatibility information.'	
CFGUndefinedError	26	0	'SCEE026 - Compatibility error. Please contact Genesys Technical Support.'	CFGUndefinedError
CFGHistoryLogExpired	27	0	'SCEE027 - Compatibility error. Please contact Genesys Technical Support.'	CFGHistoryLogExpired
CFGForcedDisconnect	28	0	'SCEE028 - The network management system has terminated your communication session. Contact your network administrator.'	CFGForcedDisconnect
CFGReadOnlyOperationalModeActivated	29	0	'SCEE029 - Transaction rejected. The Configuration Server is currently working in Read-only mode.'	CFGReadOnlyOperationalModeActivated
CFGSetOperationalModeFailed	30	0	'SCEE030 - Operation failed. The client that activated the Read-only mode is still connected to Configuration Server.'	CFGSetOperationalModeFailed
CFGUnsupportedProperty	31	0	'SCEE031 - Unsupported object property requested. Please contact Genesys Technical Support.'	CFGUnsupportedProperty
CFGUnsupportedObject	32	0	'SCEE032 - Unsupported	CFGUnsupportedObject

Mnemonic	ID	Flag	Short Description	Log Name
			object requested. Please contact Genesys Technical Support.'	
CFGExternalAuthenticationError	35	0	'SCEE033 - Authentication request is denied.'	CFGExternalAuthenticationError
CFGLocaleItemNotChanged	34	0	'SCEE034 - Locale element can not be changed. Please contact Genesys Technical Support.'	CFGLocaleItemNotChanged
CFGLocaleItemNotFound	35	0	'SCEE035 - Locale element can not be located. Please contact Genesys Technical Support.'	CFGLocaleItemNotFound
CFGXMLParseError	36	0	'SCEE036 - Update data has invalid format. Please contact Genesys Technical Support.'	CFGXMLParseError
CFGChangePasswordDenied	37	0	'SCEE037 - Password cannot be changed. External authentication is enforced.'	CFGChangePasswordDenied
CFGUnsecureConnectionDenied	38	0	'SCEE038 - Configuration Server does not accept unsecured connection.'	CFGUnsecureConnectionDenied
CFGEmptyPasswordDenied	39	0	'SCEE038 - Password cannot be empty.'	CFGEmptyPasswordDenied