



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

GVP Documentation Supplement

cpd Service Parameters for IVR Profile Provisioning

5/11/2025

cpd Service Parameters for IVR Profile Provisioning

Use these parameters to configure Call Progress Detection (cpd):

Description	Valid values	Default value	Takes effect
cpd-allowed (CPD Allowed)			
Controls whether CPD service is allowed	true: CPD service is allowed false: CPD service is not allowed	true	immediately
cpd-capability-requirement (CPD Capability Requirement)			
This parameter specifies the required capability for when the cpd service is invoked in the context of an application.	Use this format: [cap_NameA]=[cap_ValueA1],..., [cap_ValueAm]; [cap_NameB]=[cap_ValueB1],..., [cap_ValueBn]; ; [cap_NameM]=[cap_ValueM1],..., [cap_ValueMn]; The set of [cap_NameX] must be unique.	(blank)	immediately
cpd-forbidden-respcode (CPD Forbidden Response Code)			
Expects parameter value of the form sipcode;description or just sipcode.		403	immediately
cpd-forbidden-set-alarm (Raise Alarm when CPD is Not Allowed)			
If set to true, an alarm will be raised for the corresponding policy violation	true false	false	immediately
cpd-level2-burst-limit (CPD level2 Usage Limit)			
CPD application level2 usage limit	The value must be an integer	(blank)	immediately
cpd-level3-burst-limit (CPD level3 Usage Limit)			
CPD application level3 usage limit	The value must be an integer	(blank)	immediately
cpd-usage-limit (CPD Usage Limit)			
CPD application usage limit	The value must be an integer	(blank)	immediately
cpd-usage-limit-exceeded-respcode (CPD Usage Limit Exceeded Response Code)			
Expects parameter value of the form sipcode;desc or just sipcode.		480	immediately
cpd-usage-limit-exceeded-set-alarm (Raise Alarm for CPD Usage Limit Exceeded)			

If set to true, an alarm will be raised for the corresponding policy violation	true false	false	immediately
cpd-usage-limit-per-session (CPD Usage Limit per Session)			
CPD application usage limit per call	The value must be an integer	(blank)	immediately