



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# Genesys Voice Platform

reporting Section

4/22/2025

## reporting Section

- `binding.address`
- `password`
- `username`
- `did.max_overlaps`
- `port`
- `hostname`
- `protocol`

### binding.address

**Default Value:**

**Valid Values:** An IP address.

**Changes Take Effect:** at start/restart

The interface IP address that should be used for binding the PS service.

### did.max\_overlaps

**Default Value:** 10

**Valid Values:** An integer greater than 1

**Changes Take Effect:** at start/restart

The maximum number of overlaps that can be returned from a DID overlap query.

### hostname

**Default Value:**

**Valid Values:** A hostname or fully qualified domain name.

**Changes Take Effect:** at start/restart

The hostname that should be used for accessing PS.

### password

**Default Value:**

**Valid Values:** A string

**Changes Take Effect:** at start/restart

The password for PS to perform basic HTTP authentication.

## port

**Default Value:** 8090

**Valid Values:** An integer greater than 0

**Changes Take Effect:** at start/restart

The port on which the PS receives reporting requests.

## protocol

**Default Value:** http

**Valid Values:** An integer greater than 0

**Changes Take Effect:** at start/restart

The type of communication protocol that PS uses to service reporting requests.

## username

**Default Value:**

**Valid Values:** A string

**Changes Take Effect:** at start/restart

The username for PS to perform basic HTTP authentication.