



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# Genesys Engage Digital (eServices)

Chat Server: Resource Access Point for Cassandra

4/2/2025

# Chat Server: Resource Access Point for Cassandra

This section describes the options contained in ChatServerCassandraRAP.xml. Use these options to create a Resource Access Point application for use in configuring Chat Server for high availability operation with Cassandra..

**Note:**This functionality is available in releases 8.5.104 and later.

Options for this component are contained in the following configuration sections:

- [cassandra](#)
- [encryption](#)
- [settings](#)

## Tip

In the summary table(s) below, type in the Search box to quickly find options, configuration sections, or other values, and/or click a column name to sort the table. Click an option name to link to a full description of the option. Be aware that the default and valid values are the values in effect with the latest release of the software and may have changed since the release you have; refer to the full description of the option to see information for earlier releases.

**Power users:** [Download a CSV file](#) containing default and valid values and descriptions.

The following options are configured at the application level (in other words, on the application object).

Section	Option	Default	Changes Take Effect
cassandra	<a href="#">connect-timeout</a>	5	After restart
cassandra	<a href="#">contact-points</a>	127.0.0.1	After restart
cassandra	<a href="#">enabled</a>	true	After restart
cassandra	<a href="#">keyspace</a>	genesys_chat_server	After restart
cassandra	<a href="#">password</a>		After restart
cassandra	<a href="#">port</a>	9042	After restart
cassandra	<a href="#">read-consistency</a>	quorum	After restart
cassandra	<a href="#">request-timeout</a>	12	After restart
Section	Option	Default	Changes Take Effect

---

Section	Option	Default	Changes Take Effect
cassandra	resent-delay	1	After restart
cassandra	retry-attempts	10	After restart
cassandra	username		After restart
cassandra	window-size	128	After restart
cassandra	write-consistency	quorum	After restart
encryption	client-certificate-file		After restart
encryption	client-private-key-file		After restart
encryption	enabled	false	After restart
encryption	password		After restart
encryption	trusted-cert-dir		After restart
encryption	verify-peer-cert	true	After restart
encryption	verify-peer-identity	false	After restart
settings	leave-transcript	false	After restart
Section	Option	Default	Changes Take Effect