



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Genesys Engage Digital (eServices)

web-proxy Section

web-proxy Section

- `host`
- `password`
- `port`
- `usageType`
- `useProxy`
- `user`

host

Default Value: An empty string

Valid Values: Any alphanumeric string; for example: myProHost, 192.168.0.15

Changes Take Effect: After restart

Introduced: 8.5.200.02

Specifies the name or address of the host running the Web proxy. If not provided, an `IllegalArgumentException` message is generated. If E-mail Server is unable to connect to the host, a `MailConnectException` message is generated.

password

Default Value: An empty string

Valid Values: Any alphanumeric string

Changes Take Effect: After restart

Introduced: 8.5.200.02

Specifies the password to authenticate the user on the Web proxy. If this option is present, the **user** option must also be configured.

port

Default Value: 0

Valid Values: Any positive integer less than 65535

Changes Take Effect: After restart

Introduced: 8.5.200.02

Specifies the port on which the Web proxy is running. If the port number is absent or invalid, an `IllegalArgumentException` message is generated explaining the error.

usageType

Default Value: both

Valid Values: both, auth, graph

Changes Take Effect: After restart

Introduced: 8.5.203.03

Specifies how the web-proxy is used. It can be used for either authentication or Graph API. It can be used for both.

useProxy

Default Value: false

Valid Values: true, false

Changes Take Effect: After restart

Introduced: 8.5.200.02

Enables (true) or disables (false) the Web proxy.

user

Default Value: An empty string

Valid Values: Any alphanumeric string

Changes Take Effect: After restart

Introduced: 8.5.200.02

Specifies the user name to be authenticated on the Web proxy. If this option is present, the **password** option must also be configured.