



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

## Outbound Contact

isdn Section

9/7/2025

## isdn Section

- [called-party-number-plan](#)
- [called-party-number-type](#)
- [calling-party-number](#)
- [calling-party-number-plan](#)
- [calling-party-number-type](#)
- [engage-cpd-on-call-setup](#)
- [isdn-trace](#)
- [isdn-trace-file-name-prefix](#)
- [presentation-indicator](#)
- [use-channel-state](#)
- [user-info-layer-1](#)

This content is under development and might not be comprehensive or completely up to date. For full information, see [Configuration Options](#) in the *Deployment Guide*.

### called-party-number-plan

**Default Value:** isdn

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

Identifies the number plan of the party called.

### called-party-number-type

**Default Value:** national

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

Indicates the type of number for the party called.

### calling-party-number

**Default Value:**

**Valid Values:** Any digit string not longer than 31 characters

**Changes Take Effect:** Takes effect immediately

Specifies the number of the calling party.

## calling-party-number-plan

**Default Value:** isdn

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

Identifies the number plan of the calling party.

## calling-party-number-type

**Default Value:** national

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

Indicates the type of number for the calling party.

## engage-cpd-on-call-setup

**Default Value:** false

**Valid Values:** Yes/True or No/False

**Changes Take Effect:** Takes effect immediately

Instructs the CPD Server to engage in Call Progress Analysis during the ISDN call setup.

## isdn-trace

**Default Value:** false

**Valid Values:** Yes/True or No/False

**Changes Take Effect:** Takes effect immediately

Specifies whether CPD Server creates an ISDN board resource (d-channel) trace log (value = yes or true) or does not create this trace log (value = no or false).

## isdn-trace-file-name-prefix

**Default Value:** isdn\_

**Valid Values:** Any string.

**Changes Take Effect:** Takes effect immediately

Specifies the prefix for the ISDN trace file.

## presentation-indicator

**Default Value:** restricted

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

Specifies whether a presentation indicator (Caller\_ID) is allowed, restricted, or not available for an ISDN call-setup message.

## use-channel-state

**Default Value:** false

**Valid Values:** Yes/True or No/False

**Changes Take Effect:** Takes effect immediately

Specifies whether CPD Server uses a channel state (value = yes or true) or does not use a channel state (value = no or false). If yes or true, an in-service message is sent to the switch through the d-channel (ISDN line). Available in North America only.

## user-info-layer-1

**Default Value:** g711-ulaw

**Valid Values:** Please select value from the list

**Changes Take Effect:** Takes effect immediately

CPD Server reads the value of this option from the ISDN section of its application object and applies the value to the user info layer 1 field in the ISDN call setup message.