



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Skype for Business

UCMA Connector

12/19/2025

UCMA Connector

UCMA Connector reads its initial configuration from the **connector.config** configuration file instead of using an Application object. For more information about the options in the **connector.config** configuration file, see the [Deployment Guide](#).

After connecting to T-Server, UCMA Connector may receive from T-Server additional configuration options read from the **Annex** tab of the **Switch** object. Some options can be specified both in the **connector.config** configuration file and in the **Annex** tab of the Switch object. In this case, the value read from the **Annex** tab of the Switch object is used.

Switch

The following options are configured at the Switch level (in other words, on the Switch object).

Section	Option	Default	Changes Take Effect
conference-services	count	No default value	After restart of connection to UCMA Connector
conference-services	lobby-bypass-enabled	True	For next scheduled conference
conference-services	uri-pattern	No default value	After restart of connection to UCMA Connector
connector	caching-enabled	1	Immediately
connector	conf-session-shutdown	false	Immediately
connector	conference-pool-size	0	Immediately
connector	music-on-hold-file-path		Immediately
connector	musicOnHoldFilePath	No default value	Immediately
connector	reuse-avcall	0	Immediately
connector	ringtone-file-path	No default value	Immediately
Section	Option	Default	Changes Take Effect