



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Platform SDK Developer's Guide

TKVListAddBinary

5/2/2025

Contents

- [1 TKVListAddBinary](#)
 - [1.1 Description](#)
 - [1.2 Syntax](#)
 - [1.3 Parameters](#)
 - [1.4 Return Values](#)

TKVListAddBinary

Description

Adds one data item of binary type (that is, a specified number of unsigned characters), specified as the parameters `key` and `value`, to the data structure specified by the parameter `list`.

Syntax

```
TKVResult TKVListAddBinary(  
    TKVList *list,  
    char *key,  
    unsigned char *val,  
    int length  
);
```

Parameters

For basic type information for each parameter, consult the Syntax section, above.

Name	Description
<code>list</code>	A pointer to the data structure to which the specified key-value pair should be added.
<code>key</code>	A pointer to the string representing the parameter name.
<code>val</code>	A pointer to the value of the parameter specified by the parameter <code>key</code> .
<code>length</code>	The length of the parameter specified by the parameter <code>val</code> .

Return Values

Refer to the type `TKVResult`.