



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Configuration Layer Objects Reference Guide

CfgDNGroupType

CfgDNGroupType

Values

Mnemonic	ID	Flag	Short Description	Log Name	Long Description
CFGNoDNGroup	0	0	'Unknown Group Type'	Unknown	The value of the corresponding parameter has not changed.
CFGSinglePorts	1	0	'Single Ports'	SinglePorts	Can include DNs of the following types: CFGExtension, CFGACDPosition, CFGGEAPort, CFGVoiceMail, CFGCP, CFGMusic, CFGData, CFGFAX, CFGCommDN, CFGEmal, CFGVoIP, CFGVideo, CFGChat, CFGCoBrowse.
CFGACDQueues	2	0	'ACD Queues'	ACDQueues	Can only include DNs of CFGACDQueue, CFGVirtACDQueue, and CFGRoutingQueue type.
CFGRoutingPoints	3	0	'Routing Points'	RoutingPoints	Can include DNs of the following types: CFGRoutingPoint, CFGExtRoutingPoint, CFGVirtRoutingPoint, and CFGRoutingQueue.
CFGNetworkPorts	4	0	'Network Ports'	NetworkPorts	Can only include DNs of CFGDestinationLabel type.

Mnemonic	ID	Flag	Short Description	Log Name	Long Description
CFGServiceNumbers	5	0	'Service Numbers'	ServiceNumbers	Can only include DNs of CFGServiceNumber type.