



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# SIP Voicemail User Guide

Accessing Your Voicemail Account

---

## Contents

- 1 Accessing Your Voicemail Account
  - 1.1 Accessing Your Voicemail with a Local Desktop Telephone
  - 1.2 Accessing Your Voicemail with a Remote Telephone
  - 1.3 Accessing Your Voicemail in a Web Browser
  - 1.4 Listening to Your Voicemail
  - 1.5 First Time User Setup (Enrollment)

# Accessing Your Voicemail Account

## Accessing Your Voicemail with a Local Desktop Telephone

Your telephone may have a Message Waiting Indicator (MWI) in the form of a light or an LED display, which indicates that this phone's mailbox has new messages waiting.

1. Press the voicemail key, if there is one on your phone, or dial the voicemail access number. Your method of access will depend upon your specific telephone model.
2. Enter your password, if required.

### Next Steps

 [Listening to Your Voicemail](#)

 [First Time User Setup \(Enrollment\)](#)

 [Managing Your Mailbox](#)

## Accessing Your Voicemail with a Remote Telephone

1. Call the voicemail access number.
2. Enter your mail box number.
3. Enter your password.
4. Press # to confirm.

### Next Steps

 [Listening to Your Voicemail](#)

 [First Time User Setup \(Enrollment\)](#)

 [Managing Your Mailbox](#)

## Accessing Your Voicemail in a Web Browser

### Prerequisites

The computer that you are using and the host server where Genesys SIP Voicemail is installed must both be on the same LAN, or both connected to the internet.

1. Open a web browser and enter the following UID in the Address field:  
http://<hostname>:<port>/fs/admin  
...where <hostname> is the server where Genesys SIP Voicemail is installed and <port> is 8080 (Genesys SIP Voicemail's default HTTP port).
2. Enter your mailbox number and password into the corresponding fields in the dialog box. For example:
  - Mail Box: 201
  - Password: 201

### Next Steps

 [Using Web Interface](#)

## Listening to Your Voicemail

Use these commands to hear and manage your voicemail.

### Prerequisites

- You have accessed your personal voicemail mailbox ([desktop](#), [remote](#), or [browser](#)).
1. Access your mailbox, giving your mailbox number and password if necessary.
  2. Press 1 to start playing the first message.
  3. Use these commands while any message plays.
    - Press 1 to rewind 10 seconds.
    - Press 2 to pause or resume.
    - Press 3 to forward 10 seconds.
    - Press 4 to play a voice menu, which lists all commands for listeners.
    - Press 5 to hear envelope information about the call, for example: message length (in H:M:S) and Caller ID of sender.
    - Press 7 to delete.
    - Press # to go to the next message.
    - Press \* to cancel and return to main menu.

If you listen to all or part of a message and do not delete it, the message is automatically saved.

## First Time User Setup (Enrollment)

On your first login, Genesys SIP Voicemail asks you to record your name and change your password (the default matches your mailbox number).

### Prerequisites

- You have accessed your personal voicemail mailbox ([desktop](#), [remote](#), or [browser](#)).
1. Respond to the voice prompts to record your name and change your password.  
You can also change your password later, but not your name.
  2. Listen to your messages or hang up.