



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# Web Services API Reference

SwitchToBargelIn

5/5/2025

# SwitchToBargeIn

This operation is part of the [Voice API](#) section of the [Web Services API](#).

## Overview

Switches to barge for the current call. This operation is only available if the current monitoring mode is either [ListenIn](#) or [Coach](#). If the supervisor switches from Coach to BargeIn, they cannot return to Coach and can only move to ListenIn.

<b>Request URL</b>	/api/v2/me/calls/{id}
<b>HTTP method</b>	POST
<b>Required features</b>	api-voice, api-supervisor-monitoring

## Parameters

Parameter	Value
operationName	SwitchToBargeIn

## Sample

### Request

```
POST api/v2/me/calls/011DJV5JI898NB2L04000VTAES000000I
{
  "operationName": "SwitchToBargeIn"
}
```

### HTTP response

```
{
  "statusCode": 0
}
```

## CometD notification

**Important**

Note that mute now has a value of Off.

```
{
  "data":{
    "notificationType":"StatusChange",
    "call":{
      "id":"011DJV5JI898NB2L04000VTAES00000I",
      "state":"Established",
      "callUuid":"011DJV5JI898NB2L04000VTAES00000I",
      "connId":"007102385535e00e",
      "deviceUri":"http://127.0.0.1:8080/api/v2/devices/efelab32-53f9-43ce-
b65e-5768c61f7d4a",
      "participants":[
        {
          "e164Number":"",
          "formattedPhoneNumber":"5000",
          "phoneNumber":"5000",
          "digits":"5000"
        },
        {
          "e164Number":"",
          "formattedPhoneNumber":"5001",
          "phoneNumber":"5001",
          "digits":"5001"
        }
      ],
      "dnis":"5001",
      "callType":"Internal",
      "capabilities":[
        "AttachUserData",
        "InitiateConference",
        "UpdateUserData",
        "Hold",
        "SingleStepTransfer",
        "DeleteUserData",
        "SingleStepConference",
        "Hangup",
        "DeleteUserDataPair",
        "SendDtmf",
        "InitiateTransfer",
        "SwitchToListenIn",
        "RemoveParticipantFromConference"
      ],
      "duration":"21",
      "mute":"Off",
      "supervisorListeningIn":false,
      "monitoredUserMuted":false,
      "uri":"http://127.0.0.1:8080/api/v2/me/calls/011DJV5JI898NB2L04000VTAES00000I",
      "path":"/calls/011DJV5JI898NB2L04000VTAES00000I"
    },
    "phoneNumber":"5005",
    "extensions":{
      "WrapUpTime":0,
      "BusinessCall":0
    }
  }
}
```

```
    },  
    "messageType": "CallStateChangeMessage"  
  },  
  "channel": "/v2/me/calls"  
}
```