



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

Web Services API Reference

SendDTMF

12/15/2025

SendDTMF

This operation is part of the [Voice API](#) section of the [Web Services API](#).

Overview

Sends the provided DTMF digits. You can send DTMF digits individually with multiple requests or together with multiple digits in one request.

Important

If your solution uses SIP Server, you might need to set the **sip-dtmf-send-rtp** option to `true` for this request to succeed. Consult the [SIP Server documentation](#) for details.

Request URL	/api/v2/me/calls/{id}
HTTP method	POST
Required features	api-voice

Parameters

Parameter	Value
operationName	SendDtmf
digits	A string consisting of one or more digits (0-9).

Sample

Request

```
POST api/v2/me/calls/012PUFMMS0ASNAK4807GK2LAES00000J
{
  "operationName": "SendDtmf",
  "digits": "5"
}
```

HTTP response

```
{
  "statusCode": 0
}
```

CometD notification

```
{
  "data":{
    "notificationType":"DtmfSent",
    "call":{
      "id":"012PUFMMS0ASNAK4807GK2LAES00000J",
      "state":"Established",
      "callUuid":"012PUFMMS0ASNAK4807GK2LAES00000J",
      "connId":"007102719260b013",
      "deviceUri":"http://127.0.0.1:8080/api/v2/devices/631608b3-ceb1-472b-ba05-2ae39555b0d1",
      "participants":[
        {
          "e164Number":"",
          "formattedPhoneNumber":"15001",
          "phoneNumber":"15001",
          "digits":"15001"
        }
      ],
      "dnis":"15000",
      "callType":"Internal",
      "capabilities":[
        "SingleStepTransfer",
        "InitiateConference",
        "Hold",
        "SingleStepConference",
        "InitiateTransfer",
        "SendDtmf",
        "DeleteUserData",
        "AttachUserData",
        "DeleteUserDataPair",
        "Hangup",
        "UpdateUserData"
      ],
      "duration":"27",
      "mute":"Off",
      "supervisorListeningIn":false,
      "monitoredUserMuted":false,
      "monitoring":false,
      "uri":"http://127.0.0.1:8080/api/v2/me/calls/012PUFMMS0ASNAK4807GK2LAES00000J",
      "path":"/calls/012PUFMMS0ASNAK4807GK2LAES00000J"
    },
    "phoneNumber":"15000",
    "extensions":{
      "BusinessCall":0
    },
    "messageType":"CallStateChangeMessage"
  },
  "channel":"/v2/me/calls"
}
```