



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

## Outbound Contact Deployment Guide

[Correlation Between CPD Server Options and Dialogic Boards](#)

# Correlation Between CPD Server Options and Dialogic Boards

This section provides information on the correlation between CPD Server options, Dialogic Board types, and Dialer modes.

In the tables, note the following:

- No indicates that the option is not used in the given Dialing Mode / Board Type / Line-Type.
- Yes indicates that the Option is used in the given Dialing Mode / Board Type / Line-Type.
- A dash (-) indicates that the Dialing Mode / Board Type / Line-Type combination is not possible.

## ASM Dialer Mode

The section provides correlation information on the ASM (Active Switching Matrix) Dialer Mode for the following board types (see the accompanying tables):

- DMV
- JCT
- HMP

**DMV Dialogic Board Type**

Section	CPD Server Option	analogue line-type	line-side line-type	line-side-dm3 line-type	isdn line-type	isdn-dm3 line-type	cas-dm3 line-type	sip-hmp line type	sip-hmp-asm line-type
tones	busy-tone-1	—	—	—	—	No	No	—	—
	busy-tone-2	—	—	—	—	No	No	—	—
	extra-dial-tone	—	—	—	—	No	No	—	—
	fax-tone-1	—	—	—	—	No	No	—	—
	fax-tone-2	—	—	—	—	No	No	—	—
	intl-dial-tone	—	—	—	—	No	No	—	—
	local-dial-tone	—	—	—	—	No	No	—	—
	ring-	—	—	—	—	No	No	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	back-tone-1								
	ring-back-tone-2	—	—	—	—	No	No	—	—
	disconnect-tone	—	—	—	—	No	No	—	—
	forth-tone	—	—	—	—	Yes	Yes	—	—
	sit-tone	—	—	—	—	No	No	—	—
AM-beep-tones	am-beep-tone-<n>	—	—	—	—	Yes	Yes	—	—
line-side	off-hook-bit-mask	—	—	—	—	No	No	—	—
	on-hook-bit-mask	—	—	—	—	No	No	—	—
	rcv-idle-bit-mask	—	—	—	—	No	No	—	—
	snd-idle-bit-mask	—	—	—	—	No	No	—	—
isdn	called-party-number-plan	—	—	—	—	No	No	—	—
	called-party-number-type	—	—	—	—	No	No	—	—
	calling-party-number	—	—	—	—	Yes	Yes	—	—
	calling-party-number-plan	—	—	—	—	No	No	—	—
	calling-party-number-type	—	—	—	—	No	No	—	—
	isdn-	—	—	—	—	No	No	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	trace								
	isdn-trace-file-name-prefix	—	—	—	—	No	No	—	—
	presentation-indicator	—	—	—	—	No	No	—	—
	use-channel-state	—	—	—	—	Yes	Yes	—	—
	engage-cpd-on-call-setup	—	—	—	—	No	No	—	—
	user-info-layer-1	—	—	—	—	No	No	—	—
hmp	audio-codecs	—	—	—	—	No	No	—	—
	sip-local-address	—	—	—	—	No	No	—	—
	sip-proxy	—	—	—	—	No	No	—	—
general	am-beep-detect	—	—	—	—	Yes	Yes	—	—
	am-beep-detect-timeout	—	—	—	—	Yes	Yes	—	—
	continuous-no-signal	—	—	—	—	No	No	—	—
	conversation-file-name-prefix	—	—	—	—	Yes	Yes	—	—
	cpd-file-name-prefix	—	—	—	—	Yes	Yes	—	—
	cpd-recording	—	—	—	—	Yes	Yes	—	—
	cpd-if-established	—	—	—	—	No	No	—	—
	destination-busy-	—	—	—	—	Yes	Yes	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	timeout								
keep-channels-open	—	—	—	—	—	No	No	—	—
line-type	—	—	—	—	—	Yes	Yes	—	—
location	—	—	—	—	—	Yes	Yes	—	—
max-number-ports-to-record	—	—	—	—	—	Yes	Yes	—	—
off-hook-delay	—	—	—	—	—	No	No	—	—
off-hook-timeout	—	—	—	—	—	No	No	—	—
on-hook-timeout	—	—	—	—	—	No	No	—	—
out-of-service-attempts	—	—	—	—	—	Yes	Yes	—	—
out-of-service-timeout	—	—	—	—	—	Yes	Yes	—	—
pre-connect-cpd-priority	—	—	—	—	—	No	No	—	—
post-connect-cpd-priority	—	—	—	—	—	No	No	—	—
sit-detection	—	—	—	—	—	Yes	Yes	—	—
tscall	—	—	—	—	—	No	No	—	—
tsclear	—	—	—	—	—	No	No	—	—
use-busy2-as-nu-tone	—	—	—	—	—	No	No	—	—
use-fax2-as-am-tone	—	—	—	—	—	No	No	—	—
use-engaging-lines	—	—	—	—	—	Yes	Yes	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	wait-off-hook	—	—	—	—	No	No	—	—
<b>JCT Dialogic Board Type</b>									
Section	CPD Server Option	analogue line-type	line-side line-type	line-side-dm3 line-type	isdn line-type	isdn-dm3 line-type	cas-dm3 line-type	sip-hmp line type	sip-hmp-asm line-type
tones	busy-tone-1	—	—	—	Yes	—	—	—	—
	busy-tone-2	—	—	—	Yes	—	—	—	—
	extra-dial-tone	—	—	—	Yes	—	—	—	—
	fax-tone-1	—	—	—	Yes	—	—	—	—
	fax-tone-2	—	—	—	Yes	—	—	—	—
	intl-dial-tone	—	—	—	Yes	—	—	—	—
	local-dial-tone	—	—	—	Yes	—	—	—	—
	ring-back-tone-1	—	—	—	Yes	—	—	—	—
	ring-back-tone-2	—	—	—	Yes	—	—	—	—
	disconnect-tone	—	—	—	Yes	—	—	—	—
	forth-tone	—	—	—	Yes	—	—	—	—
	sit-tone	—	—	—	Yes	—	—	—	—
line-side	off-hook-bit-mask	—	—	—	No	—	—	—	—
	on-hook-bit-mask	—	—	—	No	—	—	—	—
	rcv-idle-bit-mask	—	—	—	No	—	—	—	—
	snd-idle-bit-mask	—	—	—	No	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	called-party-number-plan	—	—	—	Yes	—	—	—	—
	called-party-number-type	—	—	—	Yes	—	—	—	—
	calling-party-number	—	—	—	Yes	—	—	—	—
	calling-party-number-plan	—	—	—	Yes	—	—	—	—
isdn	calling-party-number-type	—	—	—	Yes	—	—	—	—
	isdn-trace	—	—	—	Yes	—	—	—	—
	isdn-trace-file-name-prefix	—	—	—	Yes	—	—	—	—
	presentation-indicator	—	—	—	Yes	—	—	—	—
	use-channel-state	—	—	—	Yes	—	—	—	—
	engage-cpd-on-call-setup	—	—	—	Yes	—	—	—	—
	user-info-layer-1	—	—	—	Yes	—	—	—	—
	audio-codecs	—	—	—	No	—	—	—	—
	sip-proxy	—	—	—	No	—	—	—	—
general	continuous-no-signal	—	—	—	Yes	—	—	—	—
	conversation-file-name-prefix	—	—	—	Yes	—	—	—	—

---

## Correlation Between CPD Server Options and Dialogic Boards

---

	cpd-file-name-prefix	—	—	—	Yes	—	—	—	—
	cpd-recording	—	—	—	Yes	—	—	—	—
	cpd-if-established	—	—	—	No	—	—	—	—
	destination-busy-timeout	—	—	—	Yes	—	—	—	—
	keep-channels-open	—	—	—	Yes	—	—	—	—
	line-type	—	—	—	Yes	—	—	—	—
	location	—	—	—	Yes	—	—	—	—
	max-number-ports-to-record	—	—	—	Yes	—	—	—	—
	off-hook-delay	—	—	—	No	—	—	—	—
	off-hook-timeout	—	—	—	No	—	—	—	—
	on-hook-timeout	—	—	—	No	—	—	—	—
	out-of-service-attempts	—	—	—	Yes	—	—	—	—
	out-of-service-timeout	—	—	—	Yes	—	—	—	—
	pre-connect-cpd-priority	—	—	—	Yes	—	—	—	—
	post-connect-cpd-priority	—	—	—	Yes	—	—	—	—
	sit-detection	—	—	—	Yes	—	—	—	—
	tscall	—	—	—	No	—	—	—	—
	tsclear	—	—	—	No	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	use-busy2-as-nu-tone	—	—	—	No	—	—	—	—
	use-fax2-as-am-tone	—	—	—	No	—	—	—	—
	use-engaging-lines	—	—	—	Yes	—	—	—	—
	wait-off-hook	—	—	—	No	—	—	—	—

**HMP Dialogic Board Type**

Section	CPD Server Option	analogue line-type	line-side line-type	line-side-dm3 line-type	isdn line-type	isdn-dm3 line-type	cas-dm3 line-type	sip-hmp line type	sip-hmp-asm line-type
tones	busy-tone-1	—	—	—	—	—	—	—	No
	busy-tone-2	—	—	—	—	—	—	—	No
	extra-dial-tone	—	—	—	—	—	—	—	No
	fax-tone-1	—	—	—	—	—	—	—	No
	fax-tone-2	—	—	—	—	—	—	—	No
	intl-dial-tone	—	—	—	—	—	—	—	No
	local-dial-tone	—	—	—	—	—	—	—	No
	ring-back-tone-1	—	—	—	—	—	—	—	No
	ring-back-tone-2	—	—	—	—	—	—	—	No
	disconnect-tone	—	—	—	—	—	—	—	No
	forth-tone	—	—	—	—	—	—	—	Yes
	sit-tone	—	—	—	—	—	—	—	No
AM-beep-tones	am-beep-tone-<n>	—	—	—	—	—	—	—	Yes

## Correlation Between CPD Server Options and Dialogic Boards

---

	off-hook-bit-mask	—	—	—	—	—	—	—	No
line-side	on-hook-bit-mask	—	—	—	—	—	—	—	No
	rcv-idle-bit-mask	—	—	—	—	—	—	—	No
	snd-idle-bit-mask	—	—	—	—	—	—	—	No
isdn	called-party-number-plan	—	—	—	—	—	—	—	No
	called-party-number-type	—	—	—	—	—	—	—	No
	calling-party-number	—	—	—	—	—	—	—	Yes
	calling-party-number-plan	—	—	—	—	—	—	—	No
	calling-party-number-type	—	—	—	—	—	—	—	No
	isdn-trace	—	—	—	—	—	—	—	No
	isdn-trace-file-name-prefix	—	—	—	—	—	—	—	No
	presentation-indicator	—	—	—	—	—	—	—	No
	use-channel-state	—	—	—	—	—	—	—	No
	engage-cpd-on-call-setup	—	—	—	—	—	—	—	No
	user-	—	—	—	—	—	—	—	No

## Correlation Between CPD Server Options and Dialogic Boards

---

	info-layer-1								
hmp	audio-codecs	—	—	—	—	—	—	—	Yes
	sip-local-address	—	—	—	—	—	—	—	Yes
	sip-proxy	—	—	—	—	—	—	—	Yes
general	am-beep-detect	—	—	—	—	—	—	—	Yes
	am-beep-detect-timeout	—	—	—	—	—	—	—	Yes
	continuous-no-signal	—	—	—	—	—	—	—	Yes
	conversation-file-name-prefix	—	—	—	—	—	—	—	Yes
	cpd-file-name-prefix	—	—	—	—	—	—	—	Yes
	cpd-recording	—	—	—	—	—	—	—	Yes
	cpd-if-established	—	—	—	—	—	—	—	No
	destination-busy-timeout	—	—	—	—	—	—	—	Yes
	keep-channels-open	—	—	—	—	—	—	—	No
	line-type	—	—	—	—	—	—	—	Yes
	location	—	—	—	—	—	—	—	Yes
	max-number-ports-to-record	—	—	—	—	—	—	—	Yes
	off-hook-delay		—	—	—	—	—	—	No
	off-		—	—	—	—	—	—	No

	hook-timeout								
	on-hook-timeout	—	—	—	—	—	—	—	No
	out-of-service-attempts	—	—	—	—	—	—	—	Yes
	out-of-service-timeout	—	—	—	—	—	—	—	Yes
	pre-connect-cpd-priority	—	—	—	—	—	—	—	No
	post-connect-cpd-priority	—	—	—	—	—	—	—	No
	sit-detection	—	—	—	—	—	—	—	Yes
	tscall	—	—	—	—	—	—	—	No
	tsclear	—	—	—	—	—	—	—	No
	use-busy2-as-nu-tone	—	—	—	—	—	—	—	No
	use-fax2-as-am-tone	—	—	—	—	—	—	—	No
	use-engaging-lines	—	—	—	—	—	—	—	Yes
	wait-off-hook	—	—	—	—	—	—	—	No

## Transfer Mode (TM) Dialer Mode

The section provides correlation information on the TM Dialer Mode for the following board types (see the accompanying tables):

- DMV
- JCT
- HMP

### DMV Dialogic Board Type

Section	CPD	analogue	line-side	line-side-	isdn line-	isdn-dm3	cas-dm3	sip-hmp	sip-hmp-

## Correlation Between CPD Server Options and Dialogic Boards

---

	Server Option	line-type	line-type	dm3 line-type	type	line-type	line-type	line type	asm line-type
tones	busy-tone-1	—	—	No	—	—	—	—	—
	busy-tone-2	—	—	No	—	—	—	—	—
	extra-dial-tone	—	—	No	—	—	—	—	—
	fax-tone-1	—	—	No	—	—	—	—	—
	fax-tone-2	—	—	No	—	—	—	—	—
	intl-dial-tone	—	—	No	—	—	—	—	—
	local-dial-tone	—	—	No	—	—	—	—	—
	ring-back-tone-1	—	—	No	—	—	—	—	—
	ring-back-tone-2	—	—	No	—	—	—	—	—
	disconnect-tone	—	—	No	—	—	—	—	—
	forth-tone	—	—	No	—	—	—	—	—
	sit-tone	—	—	No	—	—	—	—	—
AM-beep-tones	am-beep-tone-<n>	—	—	Yes	—	—	—	—	—
line-side	off-hook-bit-mask	—	—	No	—	—	—	—	—
	on-hook-bit-mask	—	—	No	—	—	—	—	—
	rcv-idle-bit-mask	—	—	No	—	—	—	—	—
	snd-idle-bit-mask	—	—	No	—	—	—	—	—

---

## Correlation Between CPD Server Options and Dialogic Boards

---

	called-party-number-plan	—	—	No	—	—	—	—	—
	called-party-number-type	—	—	No	—	—	—	—	—
	calling-party-number	—	—	No	—	—	—	—	—
	calling-party-number-plan	—	—	No	—	—	—	—	—
isdn	calling-party-number-type	—	—	No	—	—	—	—	—
	isdn-trace	—	—	No	—	—	—	—	—
	isdn-trace-file-name-prefix	—	—	No	—	—	—	—	—
	presentation-indicator	—	—	No	—	—	—	—	—
	use-channel-state	—	—	No	—	—	—	—	—
	engage-cpd-on-call-setup	—	—	No	—	—	—	—	—
	user-info-layer-1	—	—	No	—	—	—	—	—
	audio-codecs	—	—	No	—	—	—	—	—
	sip-local-address	—	—	No	—	—	—	—	—
	sip-proxy	—	—	No	—	—	—	—	—
general	am-beep-detect	—	—	Yes	—	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	am-beep-detect-timeout	—	—	Yes	—	—	—	—	—
	continuous-no-signal	—	—	No	—	—	—	—	—
	conversation-file-name-prefix	—	—	No	—	—	—	—	—
	cpd-file-name-prefix	—	—	Yes	—	—	—	—	—
	cpd-recording	—	—	Yes	—	—	—	—	—
	cpd-if-established	—	—	No	—	—	—	—	—
	destination-busy-timeout	—	—	Yes	—	—	—	—	—
	keep-channels-open	—	—	No	—	—	—	—	—
	line-type	—	—	Yes	—	—	—	—	—
	location	—	—	Yes	—	—	—	—	—
	max-number-ports-to-record	—	—	No	—	—	—	—	—
	off-hook-delay	—	—	Yes	—	—	—	—	—
	off-hook-timeout	—	—	Yes	—	—	—	—	—
	on-hook-timeout	—	—	Yes	—	—	—	—	—
	out-of-service-attempts	—	—	Yes	—	—	—	—	—
	out-of-service-timeout	—	—	Yes	—	—	—	—	—
	pre-connect-	—	—	No	—	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	cpd-priority							
	post-connect-cpd-priority	—	—	No	—	—	—	—
	sit-detection	—	—	No	—	—	—	—
	tscall	—	—	Yes	—	—	—	—
	tsclear	—	—	Yes	—	—	—	—
	use-busy2-as-nu-tone	—	—	Yes	—	—	—	—
	use-fax2-as-am-tone	—	—	Yes	—	—	—	—
	use-engaging-lines	—	—	No	—	—	—	—
	wait-off-hook	—	—	Yes	—	—	—	—

### JCT Dialogic Board Type

Section	CPD Server Option	analogue line-type	line-side line-type	line-side-dm3 line-type	isdn line-type	isdn-dm3 line-type	cas-dm3 line-type	sip-hmp line type	sip-hmp-asm line-type
tones	busy-tone-1	Yes	Yes	—	—	—	—	—	—
	busy-tone-2	Yes	Yes	—	—	—	—	—	—
	extra-dial-tone	Yes	Yes	—	—	—	—	—	—
	fax-tone-1	Yes	Yes	—	—	—	—	—	—
	fax-tone-2	Yes	Yes	—	—	—	—	—	—
	intl-dial-tone	Yes	Yes	—	—	—	—	—	—
	local-dial-tone	Yes	Yes	—	—	—	—	—	—
	ring-back-tone-1	Yes	Yes	—	—	—	—	—	—
	ring-back-tone-2	Yes	Yes	—	—	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	disconnect-tone	Yes	Yes	—	—	—	—	—	—
	forth-tone	Yes	No	—	—	—	—	—	—
	sit-tone	Yes	Yes	—	—	—	—	—	—
line-side	off-hook-bit-mask	No	Yes	—	—	—	—	—	—
	on-hook-bit-mask	No	Yes	—	—	—	—	—	—
	rcv-idle-bit-mask	No	Yes	—	—	—	—	—	—
	snd-idle-bit-mask	No	Yes	—	—	—	—	—	—
isdn	called-party-number-plan	No	No	—	—	—	—	—	—
	called-party-number-type	No	No	—	—	—	—	—	—
	calling-party-number	No	No	—	—	—	—	—	—
	calling-party-number-plan	No	No	—	—	—	—	—	—
	calling-party-number-type	No	No	—	—	—	—	—	—
	isdn-trace	No	No	—	—	—	—	—	—
	isdn-trace-file-name-prefix	No	No	—	—	—	—	—	—
	presentation-indicator	No	No	—	—	—	—	—	—
	use-channel-	No	No	—	—	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	state								
engage-cpd-on-call-setup	No	No	—	—	—	—	—	—	—
	user-info-layer-1	No	No	—	—	—	—	—	—
hmp	audio-codecs	No	No	—	—	—	—	—	—
	sip-proxy	No	No	—	—	—	—	—	—
general	continuous-no-signal	Yes	Yes	—	—	—	—	—	—
	conversation-file-name-prefix	No	No	—	—	—	—	—	—
	cpd-file-name-prefix	Yes	Yes	—	—	—	—	—	—
	cpd-recording	Yes	Yes	—	—	—	—	—	—
	cpd-if-established	Yes	Yes	—	—	—	—	—	—
	destination-busy-timeout	Yes	Yes	—	—	—	—	—	—
	keep-channels-open	Yes	Yes	—	—	—	—	—	—
	line-type	Yes	Yes	—	—	—	—	—	—
	location	Yes	Yes	—	—	—	—	—	—
	max-number-ports-to-record	No	No	—	—	—	—	—	—
	off-hook-delay	Yes	Yes	—	—	—	—	—	—
	off-hook-timeout	Yes	Yes	—	—	—	—	—	—
	on-hook-	Yes	Yes	—	—	—	—	—	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	timeout								
out-of-service-attempts	Yes	Yes	—	—	—	—	—	—	—
out-of-service-timeout	Yes	Yes	—	—	—	—	—	—	—
pre-connect-cpd-priority	Yes	Yes	—	—	—	—	—	—	—
post-connect-cpd-priority	Yes	Yes	—	—	—	—	—	—	—
sit-detection	Yes	Yes	—	—	—	—	—	—	—
tscall	Yes	Yes	—	—	—	—	—	—	—
tsclear	Yes	Yes	—	—	—	—	—	—	—
use-busy2-as-nu-tone	Yes	Yes	—	—	—	—	—	—	—
use-fax2-as-am-tone	Yes	Yes	—	—	—	—	—	—	—
use-engaging-lines	No	—	—	—	—	—	—	—	—
wait-off-hook	Yes	Yes	—	—	—	—	—	—	—

### HMP Dialogic Board Type

Section	CPD Server Option	analogue line-type	line-side line-type	line-side-dm3 line-type	isdn line-type	isdn-dm3 line-type	cas-dm3 line-type	sip-hmp line type	sip-hmp-asam line-type
tones	busy-tone-1	—	—	—	—	—	—	No	
	busy-tone-2	—	—	—	—	—	—	No	
	extra-dial-tone	—	—	—	—	—	—	No	
	fax-tone-1	—	—	—	—	—	—	No	
	fax-tone-2	—	—	—	—	—	—	No	
	intl-dial-tone	—	—	—	—	—	—	No	

## Correlation Between CPD Server Options and Dialogic Boards

---

	local-dial-tone	—	—	—	—	—	—	No	
	ring-back-tone-1	—	—	—	—	—	—	No	
	ring-back-tone-2	—	—	—	—	—	—	No	
	disconnect-tone	—	—	—	—	—	—	No	
	forth-tone	—	—	—	—	—	—	No	
	sit-tone	—	—	—	—	—	—	No	
AM-beep-tones	am-beep-tone-<n>	—	—	—	—	—	—	Yes	
line-side	off-hook-bit-mask	—	—	—	—	—	—	No	
	on-hook-bit-mask	—	—	—	—	—	—	No	
	rcv-idle-bit-mask	—	—	—	—	—	—	No	
	snd-idle-bit-mask	—	—	—	—	—	—	No	
isdn	called-party-number-plan	—	—	—	—	—	—	No	
	called-party-number-type	—	—	—	—	—	—	No	
	calling-party-number	—	—	—	—	—	—	No	
	calling-party-number-plan	—	—	—	—	—	—	No	—
	calling-	—	—	—	—	—	—	No	—

---

## Correlation Between CPD Server Options and Dialogic Boards

---

	party-number-type								
	isdn-trace	—	—	—	—	—	—	No	—
	isdn-trace-file-name-prefix	—	—	—	—	—	—	No	—
	presentation-indicator	—	—	—	—	—	—	No	—
	use-channel-state	—	—	—	—	—	—	No	—
	engage-cpd-on-call-setup	—	—	—	—	—	—	No	—
	user-info-layer-1	—	—	—	—	—	—	No	—
hmp	audio-codecs	—	—	—	—	—	—	Yes	—
	sip-local-address	—	—	—	—	—	—	Yes	—
	sip-proxy	—	—	—	—	—	—	Yes	—
general	am-beep-detect	—	—	—	—	—	—	Yes	—
	am-beep-detect-timeout	—	—	—	—	—	—	Yes	—
	continuous-no-signal	—	—	—	—	—	—	Yes	—
	conversation-file-name-prefix	—	—	—	—	—	—	No	—
	cpd-file-name-prefix	—	—	—	—	—	—	Yes	—
	cpd-recording	—	—	—	—	—	—	Yes	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	cpd-if-established	—	—	—	—	—	No	—
	destination-busy-timeout	—	—	—	—	—	Yes	—
	keep-channels-open	—	—	—	—	—	No	—
	line-type	—	—	—	—	—	Yes	—
	location	—	—	—	—	—	Yes	—
	max-number-ports-to-record	—	—	—	—	—	No	—
	off-hook-delay	—	—	—	—	—	No	—
	off-hook-timeout	—	—	—	—	—	No	—
	on-hook-timeout	—	—	—	—	—	No	—
	out-of-service-attempts	—	—	—	—	—	Yes	—
	out-of-service-timeout	—	—	—	—	—	Yes	—
	pre-connect-cpd-priority	—	—	—	—	—	No	—
	post-connect-cpd-priority	—	—	—	—	—	No	—
	sit-detection	—	—	—	—	—	Yes	—
	tscall	—	—	—	—	—	No	—
	tsclear	—	—	—	—	—	No	—
	use-busy2-as-nu-tone	—	—	—	—	—	No	—
	use-fax2-as-am-tone	—	—	—	—	—	No	—

## Correlation Between CPD Server Options and Dialogic Boards

---

	use-engaging-lines	—	—	—	—	—	—	No	—
	wait-off-hook	—	—	—	—	—	—	No	—