



This PDF is generated from authoritative online content, and is provided for convenience only. This PDF cannot be used for legal purposes. For authoritative understanding of what is and is not supported, always use the online content. To copy code samples, always use the online content.

# T-Server Reference Guide

TReconnectCall

4/16/2025

---

## Contents

- 1 TReconnectCall
  - 1.1 Description
  - 1.2 Parameters
  - 1.3 Return Values

# TReconnectCall

## Description

Releases the telephony object specified by the parameter `dn` from the active call specified by the parameter `current_conn_id` and retrieves the previously held call, specified by the parameter `held_conn_id`, to the same object. This function is commonly used to clear an active call and to return to a held call, or to cancel a consult call (because of no answer, called device busy, and so on) and then to return to a held call.

## Parameters

Name	Description
<code>server</code>	Local server handle to the T-Server in question.
<code>dn</code>	Directory number of the telephony object that should be reconnected to the original call.
<code>held_conn_id</code>	Connection identifier of the original call that should be retrieved.
<code>current_conn_id</code>	Connection identifier of the active call from which the telephony object in question should be released.
<code>reasons</code>	A pointer to a data structure that provides additional information associated with this action.
<code>extensions</code>	A pointer to an additional data structure.

## Return Values

Standard (See [standard-return-values](#).)